# PowerPatch® Coverage

PowerPatch® comes in several package options. To aid in project planning, the following charts have been compiled showing the coverage of each package for both linear applications and bolt sealing applications.

| PACKAGE | LINEAR COVERAGE AT ¼-IN (6 MM) DEPTH |
|---|---|
| EPCT-50 cartridge | 13 x 1-inch (33 x 2.5 cm) bead |
| EPCT-250 cartridge | 65 x 1-inch (165 x 2.5 cm) bead |
| EP paste | 18 x 1-inch (46 x 2.5 cm) bead |

| BOLT SIZE | HEAD WIDTH IN MM | COVERAGE AREA IN CM² | # OF BOLTS COVERED PER EPCT-250 | # OF BOLTS COVERED PER EPCT-50 | # OF BOLTS COVERED PER EP |
|---|---|---|---|---|---|
| M10 | 17 | 13.2 | 31 | 6 | 8 |
| M12 | 19 | 14.5 | 28 | 5 | 7 |
| M14 | 22 | 16.6 | 25 | 5 | 7 |
| M16 | 24 | 18.1 | 23 | 4 | 6 |
| M18 | 27 | 20.4 | 20 | 4 | 5 |
| M20 | 30 | 22.9 | 18 | 3 | 5 |
| M24 | 36 | 28.3 | 14 | 2 | 4 |
| M30 | 46 | 38.5 | 10 | 2 | 3 |

| BOLT SIZE IN INCHES | HEAD WIDTH IN INCHES | COVERAGE AREA IN IN² | # OF BOLTS COVERED PER EPCT-250 | # OF BOLTS COVERED PER EPCT-50 | # OF BOLTS COVERED PER EP |
|---|---|---|---|---|---|
| 5/8 | 15/16 | 2.96 | 22 | 4 | 6 |
| 3/4 | 1 1/8 | 3.53 | 18 | 3 | 5 |
| 7/8 | 1 5/16 | 4.23 | 15 | 3 | 4 |
| 1 | 1 1/2 | 4.91 | 13 | 2 | 4 |
| 1 1/8 | 1 11/16 | 5.64 | 11 | 2 | 3 |
| 1 1/4 | 1 7/8 | 6.51 | 10 | 2 | 3 |
| 1 1/2 | 2 1/4 | 8.35 | 8 | 1 | 2 |